

SCHEDA TECNICA / TECHNICAL SHEET

MXM 06

6 CH Microphone Mixer























Compact audio mixer with 6 channels for simultaneous mixing of 4 balanced signals (line or mic), 1 channel via RCA (line) and 1 digital signal (mp3 or bluetooth player). It comes with graphic 7-band equalizer and echo effect that can be applied to microphones. The first 4 channels can also manage (through XLR) condenser microphones, thanks to phantom power supply. The USB socket allows the connection to PCs to use the mixer as if it were an

It is powered by an external transformer included in the package.

Input connectors	XLR + RCA + Jack 6,3mm
Output connectors	6,3mm jack
Line inputs	6
Mic inputs	4
Number of channels	6
Graphic equalizer	Yes
Echo function	Present
Effects	send / return for external effects
Phantom Key	Yes, it allows to enable phantom power for condenser microphones
VU METERS	Yes
Pre-listening	No
Frequency response	10 Hz - 60 Khz (+/-3dB)
Voice priority function	No
Color	Grey and black
Weight	1,2
Product dimensions	260 x 190 x 55 mm
Power supply	15V DC through adaptor
Notes	bluetooth and sound card mode





Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



