

# KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

## PAA 720MBZX

720W 6 zone matrix amplifier



DOWNLOAD 

Scarica ora  
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ  
SUL NOSTRO SITO

[www.karmaitaliana.it](http://www.karmaitaliana.it)



8015439107208

Professional matrix amplifier operating on 6 zones. It features 3 mic inputs and line inputs (3 + 1 AUX) and a further channel for the MP3 module. The mic inputs have a dual connector (XLR + 6,3mm jack) and are also compatible with +48 phantom power supply. It is endowed with 4 outputs (with a RCA connectors) and a 6,3mm headphone socket on the front with specific volume control. The volume of each zone can be adjusted independently. Thanks to the multimedia panel it is possible to play Mp3 files from USB sticks or SD cards, bluetooth 5.0 signals and FM radio. Each input has its own bass and treble control and offers the possibility to connect an external alarm signal or manage it from the front button (with volume adjustment). It can be connected to an external optional control panel (model PWC 2) or to a paging microphone (model PM 2).

By pressing the RPT (repeat) key once you can scan for the DAB/FM stations.

	Yes
DC Power	24V
Bluetooth	Ver. 5.0
RMS power	360W
8 Ohm max power	720W
Impedance	8-16 Ohms
Multi zone	6 zones, each with independent volume
VU METERS	No
Tel paging function	yes
Mp3 player	Yes
Siren & Whistle	Yes
Input connectors	XLR + jack 6,3mm
Output connectors	terminals + RCA
Line inputs	3
Mic inputs	4
Constant voltage	100V compatible
Frequency response	80Hz - 16KHz
Color	black
Weight	8 kg
Product dimensions	484 x 88 x 320mm
Power supply	220V

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.