

SCHEDA TECNICA / TECHNICAL SHEET

PA 2362BT

2 x 30W stereo amplifier









This compact stereo amplifier is ideal for use in shops, receptions or homes

receptions or homes. Thanks to the back sockets it is possible to connect 2 x 30W speakers. The input signals can be mixed by means of the volume controls on the front panel and the entire mixing tone can be adjusted at will. The multimedia module offers the possibilty to play songs from SD, USB or via bluetooth.

It features 3 inputs: 2 for the connection of two microphones (via the 6.3mm mono jack on the front side) and 1 line input for external sources (such as CD players, decoders, etc.) through the RCA sockets on the back. The front panel is also equipped with SD and USB sockets with keys to play MP3 tracks. It also comes with bluetooth function to play audio from a smartphone or tablet, echo effect, balancing and bass& treble adjustment.

ktinaluskas Also FM radio and remote control.	
8 Ohm max power	2 x 16W
Input connectors	RCA + 6,3mm Jack
Output connectors	clip
Display	Yes
Frequency response	20Hz - 20kHz
RMS power	2 x 16W (4 Ohm)
SD player	Yes, included
Distortion	0,1%
nput signal level	200 mV
S/N ratio	75dB
Ohm supported	No
lax power	2 x 30W
Bridge function	No
Bluetooth	Ver. 5.0
Radio	Yes, FM
Remote control	Included
Color	Black
Weight	1,6 kg
Product dimensions	180 x 70 x 165 mm
ower supply	220V - 12V

Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



