

SCHEDA TECNICA / TECHNICAL SHEET

## **CVS 908**

Audio signal converter





DOWNLOAD ( Scarica ora il catalogo aggiornato SCOPRI TUTTE LE NOVITÀ SUL NOSTRO SITO www.karmaitaliana.it



Audio signal converter. It can transform a microphone or phono type signal into a "line" signal. For example, if you need to connect a microphone to a stereo amplifier lacking the specific connector, you can use this fixture avoiding to

Input Impedance: 50K ohms - 1kHz Input level: 0.5 mV, MIC - 3mV PHONO Gain: 50dB MIC - 34dB PHONO

Signal to noise ratio:> 48dB MIC -> 55dB PHONO Frequency Response. (MIC): +1 db-bdb 70Hz - 20kHz Equalizer (PHONO): RIAA +1 db to-3db 30Hz - 20kHz Output Level: 150mV RMS

Load Impedance:> 10K ohms Overload margin: 23dB / Crosstalk: 55dB Power supply: 12-15V DC 100mA - Polo + Central

Input connectors	RCA + 6,3mm Jack
Output connectors	RCA
Frequency response	70Hz - 20KHz
Weight	0.25
Product dimensions	135 x 70 x 40 mm
Color	Black
Power supply	12V DC through adaptor
Notes	Power adaptor included

Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



