

KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

CVS 908

Audio signal converter



Audio signal converter. It can transform a microphone or phono type signal into a "line" signal. For example, if you need to connect a microphone to a stereo amplifier lacking the specific connector, you can use this fixture avoiding to buy a mixer.

Input Impedance: 50K ohms - 1kHz
Input level: 0.5 mV, MIC - 3mV PHONO
Gain: 50dB MIC - 34dB PHONO
Signal to noise ratio:> 48dB MIC -> 55dB PHONO
Frequency Response. (MIC): +1 db-bdb 70Hz - 20kHz
Equalizer (PHONO): RIAA +1 db to-3db 30Hz - 20kHz
Output Level: 150mV RMS
Load Impedance:> 10K ohms
Overload margin: 23dB / Crosstalk: 55dB
Power supply: 12-15V DC 100mA - Polo + Central

Frequency response	70Hz - 20KHz
Output connectors	RCA
Input connectors	RCA + 6,3mm Jack
Notes	Power adaptor included
Power supply	12V DC through adaptor
Color	Black
Product dimensions	135 x 70 x 40 mm
Weight	0.25

DOWNLOAD 

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439209087

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.