

SCHEDA TECNICA / TECHNICAL SHEET

AMP 1200

2 x 1200W stereo amplifier



BRIDGE MODE









Powerful and reliable, it can be installed in a standard 19 "rack. The rear panel shows the input and output connectors as well as the limiter, ground and mode selectors to be set during installation. It is suitable to be combined with 2 or 4 passive speakers. Made entirely of metal, it is fundamental of any audio system.

4 Ohm max power	2 x 2400W
8 Ohm max power	2 x 1200W
Max bridge mode power	2400 W
Input connectors	XLR + RCA
Output connectors	Speakon + red/black wires
Rack space	2U
Cooling fan	2 fans
Display	No
Frequency response	20 Hz - 20 Khz
VU METERS	No
RMS power	2 x 600W
SD player	Not present
2 Ohm supported	No
Max power	2 x 1200W
Bridge function	Yes
Color	Black and grey
Weight	14,5
Product dimensions	482 x 370 x 88 mm
Power supply	220V





Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



