

KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

PAA 240MZ

240W 6 zone amplifier



Complete and performant PA amplifier. It can manage up to 240W of power distributed over 6 zones, each of them with independent volume control. It is possible to connect up to 6 input signals (1 mic + 3 line/mic + 2 line). Three of the four mic inputs support phantom power supply. The volume controls on the front panel are quick and practical to use. Thanks to a sophisticated multimedia module it is possible to play Mp3 tracks (via SD or USB), listen to radio stations and connect to bluetooth devices.

| | |
|---------------------------|---|
| Matrix | No |
| DC Power | 24V |
| Bluetooth | Ver. 5.0 |
| RMS power | 120W |
| Impedance | 4 - 8 - 16 Ohms |
| Multi zone | 6 zones, each with independent volume |
| VU METERS | Yes |
| Phantom Key | Yes |
| Mp3 player | Yes |
| Rack space | 2U |
| Input connectors | XLR + jack 6,3mm |
| Output connectors | Terminals |
| Line inputs | 6 (1 mic + 3 line/mic + 2 line) |
| Mic inputs | 4 (3 x XLR with phantom + 1 x 6,3mm jack) |
| Constant voltage | 70 - 100V compatible |
| Frequency response | 80Hz - 16KHz |
| Color | black |
| Weight | 9,5 kg |
| Product dimensions | 484 x 88 x 405mm |
| Power supply | 220V |

DOWNLOAD 

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439132408

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.