

KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

PAA 480MZ

6 zone 480W amplifier



Complete and performant PA amplifier. It can manage up to 480W of power distributed over 6 zones, each of them with independent volume control. It is possible to connect up to 6 input signals (1 mic + 3 line/mic + 2 line). Three of the four mic inputs support phantom power supply. The volume controls on the front panel are quick and practical to use. Thanks to a sophisticated multimedia module it is possible to play Mp3 tracks (via SD or USB), listen to radio stations and connect to bluetooth devices.

Matrix	No
DC Power	24V
Bluetooth	Ver. 5.0
RMS power	240W
Impedance	4 - 8 - 16 Ohms
Multi zone	6 zones, each with independent volume
VU METERS	Yes
Phantom Key	Yes
Mp3 player	Yes
MP3 compatible	Yes
CD/ USB	USB and SD
Rack space	2U
Input connectors	XLR + jack 6,3mm
Output connectors	Terminals
Line inputs	6 (1 mic + 3 line/mic + 2 line)
Mic inputs	4 (3 x XLR with phantom + 1 x 6,3mm jack)
Constant voltage	70 - 100V compatible
Frequency response	80Hz- 16KHz
Color	black
Weight	10 kg
Product dimensions	484 x 88 x 405
Power supply	220V

DOWNLOAD 

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439104801

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.