

SCHEDA TECNICA / TECHNICAL SHEET

PAA 480MZ

6 zone 480W amplifier


































four mic inputs support phantom power supply. The volume controls on the front panel are quick and practical to use. Thanks to a sophisticated multimedia module it is possible to play Mp3 tracks (via SD or USB), listen to radio stations and connect to bluetooth devices.

MP3 compatible	Yes
•	
Input connectors	XLR + jack 6,3mm
Output connectors	Terminals
Rack space	2U
Line inputs	6 (1 mic + 3 line/mic + 2 line)
Mic inputs	4 (3 x XLR with phantom + 1 x 6,3mm jack)
CD/ USB	USB and SD
Impedance	4 - 8 - 16 Ohms
Constant voltage	70 - 100V compatible
Multi zone	6 zones, each with independent volume
Frequency response	80Hz- 16KHz
VU METERS	Yes
Phantom Key	Yes
RMS power	240W
Mp3 player	Yes
Matrix	No
DC Power	24V
Bluetooth	Ver. 5.0
Color	black
Weight	10 kg
Product dimensions	484 x 88 x 405
Power supply	220V





Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



