

SCHEDA TECNICA / TECHNICAL SHEET

PAA 720MBZX

720W 6 zone matrix amplifier






























www.karmaitaliana.it



Professional matrix amplifier operating on 6 zones.

It features 3 mic inputs and line inputs (3 + 1 AUX) and a further channel for the MP3 module.

The mic inputs have a dual connector (XLR + 6,3mm jack) and are also compatible with +48 phantom power supply. It is endowed with 4 outputs (with a RCA connectors) and a 6,3mm headphone socket on the front with specific

volume control.

The volume of each zone can be adjusted independently Thanks to the multimedia panel it is possible to play Mp3 files from USB sticks or SD cards, bluetooth 5.0 signals and FM radio. Each input has its own bass and treble control and offers the possibility to connect an external alarm signal or manage it from the front button (with volume adjustment). It can be connected to an external optional control panel (model PWC 2) or to a paging microphone (model PM 2).

By pressing the RPT (repeat) key once you can scan for

that DARGEN stations.	XLR + jack 6,3mm
Output connectors	terminals + RCA
Line inputs	3
Mic inputs	4
Impedance	8-16 Ohms
Siren & Whistle	Yes
Constant voltage	100V compatible
Multi zone	6 zones, each with independent volume
8 Ohm max power	720W
Frequency response	80Hz - 16KHz
VU METERS	No
RMS power	360W
Mp3 player	Yes
Tel paging function	yes
Matrix	Yes
DC Power	24V
Bluetooth	Ver. 5.0
Color	black
Weight	8 kg
Product dimensions	484 x 88 x 320mm
Power supply	220V

Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



