

SCHEDA TECNICA / TECHNICAL SHEET

## **PAA 6240DMZ**

6x240W 6 zone matrix amplifier

























Professional matrix amplifier operating at 8- 16 Ohm or 100V. It can handle 3 mic inputs and 4 line inputs on 6 zones (besides the channel intended for the MP3 module). It comes with dual mic inputs (XLR + 6,3mm jack) that can be powered by +48V phantom. It is endowed with 4 outputs through RCA connectors and, on the front, a 6,3mm jack for headphone with specific volume control. Each zone has its own independent volume control. Thanks to the multimedia module it is possible to play MP3 files from USB sticks or SD cards, bluetooth signals and DAB+ radio.

It also offers the possibility to adjust bass and treble independently for each input, connect an external alarm signal or control it using the button on the front panel (with volume adjustment). It can be connected to external control panels (PWC 2) and to a paging microphone (PM

MP3 compatible	Yes	
Input connectors	XLR + jack 6,3mm	
Output connectors	Terminals	
Line inputs	3 + 1 aux	
Mic inputs	3	
Impedance	4 - 8 - 16 Ohms	
Constant voltage	100V compatible	
8 Ohm max power	6 x 240W (1440W)	
Frequency response	80Hz - 16KHz	
VU METERS	No	
Phantom Key	Yes	
RMS power	720W (6 x 120W)	
Multizone	6 zones	
Mp3 player	Yes	
Matrix	Yes	
DC Power	24V	
Bluetooth	Ver. 5.0	
Color	black	
Weight	8 kg	
Product dimensions	448 x 88 x 405	
Power supply	220V	





www.karmaitaliana.it



Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



