

SCHEDA TECNICA / TECHNICAL SHEET

PAA 225BMZ

225W 3 zone amplifier

























PA amplifier designed for installation in 2U rack space. Very versatile thanks to its 225W power that can be split into 3 zones with independent volume control.

It supports 3 microphones and 2 line signal, but it can also play MP3 tracks and radio stations. Thanks to its bluetooth receiver it can be connected to smartphones and tablets. Two microphones can be powered by +48V phantom. It includes a DINDON microphone.

It also features mute function, dual siren effect with adjustable volume and master control of bass and treble.

MP3 compatible	Yes
Input connectors	XLR + RCA + Jack 6,3mm
Output connectors	Terminals
Rack space	2U
Line inputs	2
Mic inputs	3
Impedance	4 - 8 - 16 Ohms
Siren & Whistle	ding-dong + siren
Constant voltage	70 - 100V compatible
Multi zone	3 zones
8 Ohm max power	225W
Frequency response	80Hz - 16KHz
VU METERS	Yes
Phantom Key	Yes
RMS power	125W
Mp3 player	Yes
Matrix	No
Bluetooth	Ver. 5.0
Color	black
Weight	7,6
Product dimensions	418 x 88 x 318 mm
Power supply	220V





Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.





