

KARMA[®]

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

PAA 225BMZ

225W 3 zone amplifier



PA amplifier designed for installation in 2U rack space. Very versatile thanks to its 225W power that can be split into 3 zones with independent volume control. It supports 3 microphones and 2 line signal, but it can also play MP3 tracks and radio stations. Thanks to its bluetooth receiver it can be connected to smartphones and tablets. Two microphones can be powered by +48V phantom. It includes a DINDON microphone. It also features mute function, dual siren effect with adjustable volume and master control of bass and treble.

Matrix	No
Bluetooth	Ver. 5.0
RMS power	125W
8 Ohm max power	225W
Impedance	4 - 8 - 16 Ohms
VU METERS	Yes
Phantom Key	Yes
Multi zone	3 zones
Mp3 player	Yes
MP3 compatible	Yes
Siren & Whistle	ding-dong + siren
Rack space	2U
Input connectors	XLR + RCA + Jack 6,3mm
Output connectors	Terminals
Line inputs	2
Mic inputs	3
Constant voltage	70 - 100V compatible
Frequency response	80Hz - 16KHz
Color	black
Weight	7,6
Product dimensions	418 x 88 x 318 mm
Power supply	220V

DOWNLOAD 

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439202255

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.