

SCHEDA TECNICA / TECHNICAL SHEET

MMX 11

11 input mixer pre-amplifier

















Rack fixture useful both as 11 input mixer and as stereo

preamplifier. It is possible to connect to the back panel up to 6 microphones (with + 48V phantom power supply) through XLR and 5 signals through RCA connectors. It is endowed with stereo output both through RCA and XLR. It can operate also powered by an external 24V better.

battery.
Priority function.

Input connectors	XLR + RCA
Output connectors	XLR + RCA
Line inputs	4 + 1 EMC
Mic inputs	6
Number of channels	6
VU METERS	Yes
Rack space	1U
Pre-listening	No
S/N ratio	>70dB
Frequency response	60 Hz - 15 KHz
Voice priority function	Yes, on MIC 1 only
Color	black
Weight	1.4
Product dimensions	483 x 440 x 100 mm
Power supply	220V - 24V

Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.





