

KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

PAA 60M2Z

60W 2-zone amplifier



PA amplifier suitable for 70/100V or low impedance operation. 100V signals can also be managed thanks to its 2 zones. It is possible to connect up to 3 microphones and 4 line signals, each with independent volume control. Phantom power and priority function can be activated on microphone 1. It is equipped with terminals for a monitor speaker and sockets for 24V power supply. The multimedia module can play MP3 songs from microSD, USB, bluetooth. It is also endowed with FM radio. The maximum power is 60W.

Matrix	No
DC Power	24V
Bluetooth	yes
RMS power	30W
Multizone	2 zones
8 Ohm max power	60W
Impedance	4 - 8 - 16 Ohms
Voice priority function	Yes, on MIC 1 only
VU METERS	Yes
Multi zone	2 zones
Tel paging function	Yes
Mp3 player	Yes
MP3 compatible	Yes
Input connectors	XLR + RCA + Jack 6,3mm
Output connectors	terminals + RCA
Line inputs	4
Mic inputs	3
Constant voltage	70 - 100V compatible
S/N ratio	Line >85dB, Mic > 72dB
Frequency response	60 Hz - 15 KHz (+/-3dB)
Color	black
Weight	3,7 kg
Product dimensions	320 x 210 x 90mm
Power supply	AC 100 -240V DC 24V
Notes	FM radio

DOWNLOAD

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439250607

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.