

KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

PAA 120M2Z

120W 2-zone amplifier



PA amplifier suitable for 70/100V or low impedance operation. 100V signals can also be managed thanks to its 2 zones. It is possible to connect up to 3 microphones and 4 line signals, each with independent volume control. Phantom power and priority function can be activated on microphone 1. It is equipped with terminals for a monitor speaker and sockets for 24V power supply. The multimedia module can play MP3 songs from microSD, USB, bluetooth. It is also endowed with FM radio. The maximum power is 120W.

| | |
|-------------------------|-------------------------|
| Matrix | No |
| DC Power | 24V |
| Bluetooth | yes |
| RMS power | 60 |
| Multizone | 2 zones |
| Impedance | 4 - 8 - 16 Ohms |
| Multi zone | 2 zones |
| Voice priority function | Yes, on MIC 1 only |
| VU METERS | Yes |
| Phantom Key | Yes |
| Tel paging function | Yes |
| Mp3 player | Yes |
| MP3 compatible | Yes |
| Input connectors | XLR + RCA + Jack 6,3mm |
| Output connectors | terminals + RCA |
| Line inputs | 4 |
| Mic inputs | 3 |
| Constant voltage | 70 - 100V compatible |
| S/N ratio | Line >85dB, Mic > 72dB |
| Frequency response | 60 Hz - 15 KHz (+/-3dB) |
| Color | Black |
| Weight | 4,2 kg |
| Product dimensions | 320 x 210 x 90 mm |
| Power supply | 220V - 24V |

DOWNLOAD

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439241209

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.