

SCHEDA TECNICA / TECHNICAL SHEET

PAA 160TMZB

160W - 5 zone PA amplifier
























independent volume.
2 aux and 3 microphone inputs can fulfil most of the necessities. Mp3 module via USB and bluetooth receiver

make this amplifier particularly versatile.

The MIC 1 input is intended only for condenser microphones with external power supply (battery or power adaptor). It is not compatible with ordinary dynamic microphones.

| Matrix | No |
|-------------------------|---------------------------------------|
| Bluetooth | yes |
| RMS power | 80 W |
| Multizone | 5 zones |
| 8 Ohm max power | 160W |
| Impedance | 4 - 8 - 16 Ohms |
| Multi zone | 5 zones, each with independent volume |
| Voice priority function | Yes |
| VU METERS | Yes |
| Phantom Key | No |
| Mp3 player | No |
| MP3 compatible | Yes |
| CD/ USB | It includes USB module with display |
| Cooling fan | 1 fan |
| Rack space | 2U |
| Input connectors | RCA + 6,3mm Jack |
| Output connectors | Terminals |
| Line inputs | 2 |
| Mic inputs | 3 |
| Constant voltage | 70 - 100V compatible |
| Color | Black |
| Weight | 7,5 kg |
| Product dimensions | 482 x 100 x 350 mm |
| Power supply | 220V |





Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



