

SCHEDA TECNICA / TECHNICAL SHEET

SET 8302LAV

Dual UHF wireless microphone with headset





Compact and efficient wireless microphone with two headset transmitters. It features 48 channels to operate in any condition. It covers a range of 50m with very good audio performance both for speech and for song. The receiver base features both a balanced XLR socket and a 6,3mm mixed socket. It can be powered from an ordinary USB socket and comes with a wide display showing all main information. Thanks to the easy change system it is possible to change the channel directly from the microphone. The transmitter is powered by 2 AA batteries (not included).

Output connectors	XLR + 6,3mm Jack
Frequency type	UHF
Display	Yes
Operating range	50m
Receiver dimensions	210 x 40 x 180mm
Headband weight	0,070 kg
Frequency response	30Hz - 20KHz
Sensitivity	-96dbm
Carrying case	Included
Color	Black
Weight	0,388
Power supply	5V DC (via power adaptor)
Notes	Frequency A: 679.100 MHz - 693.400 MHz Frequency B: 663.100 MHz - 677.400 MHz





Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.



