

SCHEDA TECNICA / TECHNICAL SHEET

DJ LED251

3 in 1 light effect





















3-in-1 lighti effect able operating in auto mode, sound-activated mode or connected to DMX system, thanks to its 12-channel interface. It comes with 3pin XLR connectors for in master/slave mode. With its 8 x RGBW leds it can create unlimited lighting combinations, but it can be used also as a strobe light with adjustable flashing frequency. It also features a faceted ball including 6 x RGBWAP LEDs that produce a myriad of moving rays with continuous colour change.

It is equipped with a ring to fix optional safety cables and a display for easy setup. The practical display overturn function allows to use the fixture upside down..

from 10 to 29 leds
XLR
XLR
12 DMX channels
Automatic + sound activation + DMX + master/slave
Yes
1 fan
Yes, from 0 to 100%
Yes
Yes
Light effect
8+6
black
2,4 kg
280 x 180 x 150mm

Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.





