

KARMA®

— GLEMM — rîdem —

SCHEDA TECNICA / TECHNICAL SHEET

BMS4000

2 x 2000W Amplifier



Stereo power amplifier capable of generating a maximum power of 2000W per channel. Fits in standard 19" racks with 2U footprint. It has RCA and Jack 6.3mm type inputs, while the outputs for the right and left channels are SPEAKON type or via normal binding posts. It has electronic overload protection and independent front volumes for the 2 channels.

4 Ohm max power	2 x 1900W
8 Ohm max power	2 x 1500W
Overload circuits	Yes
Input connectors	RCA + 6,3mm Jack
Output connectors	Speakon + terminals
Rack space	2U
Cooling fan	1 fan
Display	No
Frequency response	10Hz - 20KHz
RMS power	2 x 600W
SD player	Not present
2 Ohm supported	No
Max power	2 x 1500W
Bridge function	No
Bluetooth	No
Radio	No
Remote control	Not available
Color	black
Weight	10 kg
Product dimensions	489 x 250 x 89mm
Power supply	220V

DOWNLOAD 

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



3666630008044

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.